

| manual motor starters | | single phase motor | | | | | | | | | | | | |
|-----------------------|----------------------------|---------------------|------------------------------|---------------------|------------------------------|---------------------|------------------------------|---------------------|------------------------------|---------------------|------------------------------|---------------------|------------------------------|-----|
| Types | Adustable Current range(A) | Rated capacity (HP) | rated operational current(A) | Rated capacity (HP) | rated operational current(A) | Rated capacity (HP) | rated operational current(A) | Rated capacity (HP) | rated operational current(A) | Rated capacity (HP) | rated operational current(A) | Rated capacity (HP) | rated operational current(A) | |
| | | 110-120V | | 200V | | 208V | | 220-240V | | 440-480V | | 550-600V | | |
| BM3VSB | -010 | 6.3-10 | 1/3 | 7.2 | 3/4 | 7.9 | 3/4 | 7.6 | 3/4 | 6.9 | 3 | 8.5 | 3 | 6.8 |
| | | | | | | | 1 | 8.8 | 1 | 8.0 | | | | |
| | -013 | 9-13 | 1/2 | 9.8 | 1 | 9 | | | 1-1/2 | 10 | | | | |
| | -016 | 11-16 | 3/4 | 13.8 | 1-1/2 | 12 | 1-1/2 | 11 | 2 | 12 | 5 | 14 | 5 | 11 |
| | | | | | 2 | 14 | 2 | 13 | | | | | | |
| | -020 | 14-20 | 1 | 16.0 | | | 3 | 19 | 3 | 17 | | | 7-1/2 | 16 |
| | -025 | 19-25 | 1-1/2 | 20 | 3 | 19.6 | | | | | 7-1/2 | 21 | 10 | 20 |
| | -032 | 24-32 | 2 | 24 | | | 5 | 31 | 5 | 28 | 10 | 26 | 15 | 27 |
| -040 | 28-40 | 3 | 34 | 5 | 32.2 | | | | | 15 | 34 | 20 | 35 | |
| -050 | 35-50 | | | 7-1/2 | 46 | 7-1/2 | 44 | 7-1/2 | 40 | 20 | 44 | 25 | 44 | |
| -063 | 45-63 | 5 | 56 | 10 | 57.5 | 10 | 55 | 10 | 50 | 25 | 55 | 30 | 54 | |

