

manual motor starters		single phase motor												
Types	Adjustable Current range(A)	Rated capacity (HP)	rated operational current(A)	Rated capacity (HP)	rated operational current(A)	Rated capacity (HP)	rated operational current(A)	Rated capacity (HP)	rated operational current(A)	Rated capacity (HP)	rated operational current(A)	Rated capacity (HP)	rated operational current(A)	
		110-120V		200V		208V		220-240V		440-480V		550-600V		
BM3RSB	-P16	0.1-0.16												
	-P25	0.16-0.25												
	-P40	0.25-0.4												
	-P63	0.4-0.63												
	-001	0.63-1.0												
	-1P6	1-1.6												
	-2P5	1.6-2.5					1/6	2.4	1/10	1.5			1/2	2.0
									1/8	1.9				
	-004	2.5-4	1/10	3.0	1/6	2.5	1/4	3.2	1/6	2.2				
			1/8	3.8	1/4	3.3			1/4	2.9	1/2	2.5	3/4	2.8
	-6P3	4-6.3	1/6	4.4	1/3	4.1	1/3	4.0	1/3	3.6	3/4	3.5	1	3.2
			1/4	5.8	1/2	5.6	1/2	5.4	1/2	4.9	1	4.0	1-1/2	4.0
											1-1/2	5.0	2	4.8
	-010	6.3-10	1/3	7.2	3/4	7.9	3/4	7.6	3/4	6.9	2	6.0	3	6.8
							1	8.8	1	8.0	3	8.5		
-013	9-13	1/2	9.8	1	9.2	1	8.8	1	8.0					
-016	11-16	3/4	13.8	1-1/2	11.5	1-1/2	11.0	1-1/2	10.0	5	14	5	11.2	
				2	13.8	2	13.2	2	12.0					
-020	14-20	1	16.0			3	18.7	3	17.0			7-1/2	16	
-025	19-25	1-1/2	20	3	19.6	3	18.7	3	17.0	7-1/2	21	10	20	
-032	24-32	2	24			5	30.8	5	28.0	10	26	15	27	

